

## **TIP SHEET FOR DBAs**

You can hook up a 12v bill acceptor, the wiring isn't provided. This is a do at your own risk project.

The power comes from the J12 connector on the "+V" pin and the ground goes to the "G" that is closest to the "+V"

Depending on the FAST board revision, that connector is either 11 pins, or 13 pins.

On the 11 pin version, it's pin 7 is G and pin 11 for the +V

On the 13 pin version, it's pin 9 is G and pin 13 for the +V.

The 'switch' part of it gets connected to pin 1 of J4 and will show up as "coin 1" for settings purposes.

The ground for the switch connects to the same ground as the other coin switch on the door, which should be pin 9 on J4.